



# Designers and Manufacturers of RF Amplifiers

## RF Amplifier Data Sheet BT-DeltaA series 250W, 500W CW



The BT-DeltaA series is a range of class AB RF power amplifiers covering the 100MHz to 500MHz frequency range

- Excellent phase and amplitude stability
- Rugged, reliable, modular solid-state design
- High linearity
- In-built protection
- Very fast blanking
- Capable of pulsed operation

Suitable for CW radar, communications, HF/VHF jamming, particle accelerator/plasma systems, plasma, RF heating and other scientific applications.

### BT-DeltaA series

Model numbers	BT00250-DeltaA-CW BT00500-DeltaA-CW
Rated power	250W, 500W minimum <sup>1</sup>
P1dB	200W, 400W minimum <sup>2</sup>
Type	Class AB MOSFET
Frequency	100-500MHz
Gain flatness	±1.5dB maximum
Harmonics	Odd: -12dBc maximum Even: -20dBc maximum
Spurious	<-70dBc maximum
Output noise (blanked)	<10dB above thermal (1MHz bandwidth)
Output sample	-40dB into 50Ω
Input/output impedance	50 Ω nominal
Protection	Over temperature, load mismatch protection via automatic level control(ALC <sup>3</sup> )

### BT-DeltaA series

Indicators	DC Power Output Enable RF Power Over-temp Load mismatch
Status monitoring interface	Optional: RS232, RS422, RS485 supported
Cooling	Forced air
Drive signals: RF drive	0dBm nominal, 10dBm for no damage
RF gate (blanking)	0-5V CMOS
Physical	19" Wx 600mmD x 128mmH <sup>4</sup>
RF input signal format	CW/AM/FM/PM/pulse
Connectors	RF output: N type RF input, gate, sample: BNC
Mains power requirements	110-240V, 50-60Hz, single phase, 1kVA max. 250W 2kVA max. 500W <sup>5</sup>
Compliance	CE

1. Input power=1mW
2. Minimum output power at 1dB gain compression
3. ALC becomes active at not less than SWR 2:1 at full rated power
4. 3RU x 19" inch rack mounting
5. 3-pin IEC. Mains supply must include an earth

© Tomco Technologies





Designers and Manufacturers of RF Amplifiers

## RF Amplifier Data Sheet BT-DeltaA series, 100-500MHz

Typical normalised output power plots in dB  
BT-Delta series

